


DIRECTIONAL YAGI ANTENNAS Y(B)8966

Innovative **Technology** for a **Connected** World



GOLD SERIES DIRECTIONAL YAGI ANTENNAS PROVIDE INDUSTRY-LEADING DESIGN FEATURES WITH LONG TERM OPTIMAL PERFORMANCE

Laird Technologies' premium series directional Yagi antennas are fully gold anodized for corrosion resistance. All UHF and above frequency antennas feature internal matching to assure broad bandwidth and resistance to severe weather conditions. There is no gamma match to ice up, corrode or detune. Our engineering staff has optimized the product family for forward gain by computer analysis and then field-tested each for conformance.

FEATURES AND BENEFITS:

- All UHF and higher frequency antennas feature 360° welds around each element and an end-of-boom N connector feed with an internal transmission line feeding the driven element.
- Every Yagi is tuned on a network analyzer for best power match and lowest VSWR.
- All Yagi antennas ship complete with a high quality cast aluminum mounting kit that includes stainless steel hardware and allows vertical or horizontal orientation during installation (VHF models require light assembly).

APPLICATIONS:

- Point-to-point and multi-point / omnidirectional outdoor antennas applications used by private organizations and government agencies around the globe.
- Typical applications include transportation such as railroad switching, remote locations reporting examples that include oil fields, weather conditions and, meter data transmissions for utilities.

Electrical		Mechanical	
Frequency Range	896 – 970 MHz	Material	Aluminum
Frequency Bandwidth	74 MHz	Length	27.688″
VSWR	< 2:1	Height	6.75″
Return Loss	-10 dB max	Boom Diameter	.875″
Nominal Gain	9 dBd	Weight	3.9 lbs
Front to Back Ratio	20 dBd	Rated Wind Velocity	150 mph (241 kph)
Maximum Power	300 W	Rated Wind Velocity (with 0.5" radial ice)	80 mph (130 kph)
Nominal Impedance	50 Ω		
Polarization	Vertical or Horizontal	Equivalent Flat Area	0.2492 sq. ft.
		Cable	None
Pattern	Directional	Termination	N-Female connector
Horizontal Beamwidth	56°	Color	Gold or Black Anodized
(For Horizontal Polarization)		Lightning Protection	Lightning Arrestor LABH350NN (Sold Separately)
Vertical Beamwidth (For Vertical Polarization)	52°		
Tuning	Fixed	Mounting Included	Heavy duty cast aluminum bracket accommodates up to 2-1/2" mast
Transmitting/Receiving	Both		


global solutions: local support ...

Americas: +1.847 839.6907 IAS-AmericasEastSales@lairdtech.com


Europe: +44.(0).1628.858941 IAS-EUSales@lairdtech.com

Asia: +86.21.5855.0827.127 IAS-AsiaSales@lairdtech.com

www.lairdtech.com



Vertical-to-Vertical Polarization Azimuthal Pattern (Y, Z, or E-plane)



Horizontal-to-Horizontal Polarization Azimuthal Pattern (Y, Z, or H-plane)

ANT-DS-Y(B)8966 0812

Any information functional by Laird Technologies, Inc. and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird Technologies materials rests with the end user, since Laird Technologies and its agents cannot be aware of all potential uses. Laird Technologies materials or warrantees as to the fitness, merchantability or suitability of any Laird Technologies in a grent cannot be aware of all potential uses. Laird Technologies materials near the fitness, merchantability or suitability of any Laird Technologies materials or modures for any specific or general uses. Laird Technologies the internet all canages of any kind. All Laird Technologies materials rests, which all Laird Technologies is a constrained and ther marks are and conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2012 Laird Technologies, Inc. and Richnologies, Inc. and affect materials rests of Laird Technologies is agents and conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2012 Laird Technologies, Inc. and Richnologies, Inc. and affect material and there marks are tade marks or registreed tade marks oregistreed tade marks oregistreed tade mark